

# FDP 4.600

## Full Range Class D 4-Channel amplifier

- Small size  
Easy integration in a vehicle
- High-pass, low-pass, and band-pass crossover

- Compact Aluminum chassis  
High thermal dissipation



- 4G Power & Ground Terminals

- Remote sub control  
with LED clipping indicator

- High and low-level inputs  
Suits any installation
- "Auto Power On" with high-level input  
Easier Integration with factory head unit
- Selectable Balanced or Unbalanced inputs
- Designed & Engineered in California  
Not a "me too" amplifier design

### ADVANTAGES

- Very small size for power output
- Can be used in 2, 3, or 4 channel modes
- High-level input, compatible with OEM Stereo
- Easily accessible settings
- Remote sub control
- Invisible mounting bracket
- Highest level of crossover flexibility

### TECHNICAL CHARACTERISTICS

Power into 4 Ohms: 4x150W rms  
Power into 2 Ohms: 4x200W rms  
Bridged mode into 4 Ohms: 2x400W rms  
Frequency response: 5Hz–25kHz  
Signal/noise ratio: >95dB (A)

Adjustable gain 200mV to 19V  
Dimensions (HxLxD): 2 x 10 x 7 3/4 in  
(50x254x196mm)  
Protections: Short-circuit, continuous current,  
thermal overload, polarity reversal, DC

