

# FDP Sport

High Quality Full Range Class D amplifier using discrete components



## INCLUDED ACCESSORIES

- Harley Molex input harness
- Harley Molex output harness
- OFC power and ground cable, will reach the battery.
- Adjustable mounting feet for 2 different mounting options.
- Regular 4 channel RCA input harness

## TECHNICAL CHARACTERISTICS

Power into 4 Ohms: 4x175W rms

Power into 2 Ohms: 4x250W rms

Bridged mode into 4 Ohms: 2x500W rms

Frequency response: 20 - 30KHz +0, -1dB

Signal/noise ratio: 95dB (A)

Adjustable gain 200mV to 19V

Dimensions (HxLxD): 1-5/8 x 8-1/4 x 5 in (41x208x127mm)

Protections: Short-circuit thermal overload, polarity reversal, DC

## ADVANTAGES

- Very small size for power output
- Can be used in 2, 3, or 4 channel modes
- Conformally coated circuit board for added water resistance
- Hard anodizing for added scratch resistance.
- Flexible crossovers for every amp configuration
- Anti Hard clipping circuit

